



**PRODUCT DESCRIPTION**

Compact in size, the Studio 980T is an efficient 2.0 solution for desktops and small spaces. Producing 21W RMS from the 4 inch bass driver and 13mm tweeter, the Studio 1 can be connected to your audio devices by the two RCA input options. Master volume and bass adjustment dials are located on the back of the active speaker, allowing for a tailored listening experience.

**FEATURES**

- Active bookshelf speaker system with 24W total power output
- 100% MDF wooden enclosures to minimize acoustic resonance
- Magnetically shielded speakers
- Calibrated, flared bass reflect port in front of the speaker cabinet
- Dual RCA inputs for connectivity to multiple audio sources
- Universal 110V-240V power supply

**SPECIFICATIONS**

Total power output:	RMS 12W × 2 (THD+N=10%)
Signal to noise ratio:	≥85 dBA
THD (Total harmonic distortion):	≤ 0.5%
Frequency response:	70 HZ-20 KHZ +/-9db
Input sensitivity:	PC:700±50mV AUX:550±50mV (THD+N=1%)
Input type:	3.5mm stereo RCA
Adjustment:	Master volume and separate bass adjustment
Bass driver:	4 inch (116 mm), magnetically shielded, 6 Ω
Treble driver:	Φ13 mm silk dome, magnetically shielded, 4 Ω
Dimension:	140(W) × 226(H)× 197(D)mm

Rear view



**ORDERING DETAILS**

<b>EAN:</b> 6923520263899	<b>Model No.:</b> R980T	<b>Description:</b> 2.0 Studio speaker system
------------------------------	----------------------------	--